

WISI XE 50 FA

Diplexer 65/85 MHz



Description

Diplex filter for use in amplifiers of the product range COMPACT-LINE.

At a glance:

- passive diplex filter for use in Compact Line amplifiers
- with 65 and 85 MHz passband corner frequencies
- mirrored filter for VX50A / 0650

Technical data

| | |
|--|---------------|
| Frequency range high-pass | 85...1006 MHz |
| Frequency range low-pass | 5...65 MHz |
| characteristic impedance | 75 Ω |
| Transmission attenuation | $\leq 1,1$ dB |
| Return loss | ≥ -22 dB |
| Circulation damping (with 75 Ω Termination at port 1) | ≥ 40 dB |
| Circulation damping (without 75 Ohm Termination at port 1) | ≥ 35 dB |

Packaging data

| | |
|--------------------------------------|----------------------|
| Sales unit | pcs. |
| Dimensions (WxHxD) sales unit | 490 x 200 x 130 mm |
| Packaging volume sales unit | dm ³ |
| Gross weight sales unit | 0.010 kg |
| Shipping unit | pcs. |
| Dimensions (WxHxD) shipping unit | mm |
| Packaging volume shipping package | 0.14 dm ³ |
| Gross weight shipping unit | 0.02 kg |
| EAN | 4010056706760 |
| Article number | 70676 |
| Customs tariff number | 85291080 |